

Measurement example



Technical Explanation

Measurement procedure



A consistently low measuring force can be guaranteed by only taking measurements when the pointer is between the two fiducial lines.

Optional Accessories

Code No.	Type	Description
264-020	—	USB Input Tool Series USB Keyboard Signal Conversion Type IT-020U
959149	C	Connection cable for IT/DP/MUX (1 m)
959150	C	Connection cable for IT/DP/MUX (2 m)
06AFM380C	C	USB Input Tool Direct (2 m)
02AZD730G	IP67	U-WAVE-T
02AZD880G	Buzzer	U-WAVE-T
02AZE200	—	U-WAVE-T mounting bracket
02AZD790C	C	Connection cable for U-WAVE-T (160 mm)
02AZE140C	C	Connection cable for U-WAVE-T For foot switch
264-620	IP67	U-WAVE-TC
264-621	Buzzer	U-WAVE-TC
264-624	IP67	U-WAVE-TCB Transmitter
264-625	Buzzer	U-WAVE-TCB Transmitter
02AZF300	Buzzer	Connecting unit for U-WAVE-TC/TCB

ABSOLUTE Low Force Caliper SERIES 573

- Due to the low measuring force, this caliper is ideal for measuring elastic workpieces such as plastic parts and rubber parts.
- Easily allows fine feeding by using the thumb roller.
- Measuring force: 0.5 N to 1.0 N



573-191-30

SPECIFICATIONS

Metric				
Code No.	Range (mm)	Resolution (mm)	Maximum permissible error (mm)*	
			EMPE	SMPE
573-191-30	0 - 180	0.01	±0.05	

Inch / Metric				
Code No.	Range	Resolution	Maximum permissible error*	
			EMPE	SMPE
573-291-30	0 - 7 in/0 - 180 mm	0.0005 in/0.01 mm	±0.002 in/±0.05 mm	

- Power source: SR44 battery (1 pc.), **938882** included as standard (for operational checks)
- Position detection method: ABSOLUTE electromagnetic inductive linear encoder
- Response speed: Unlimited
- * The Partial Surface Contact Error (EMPE) and Shift Error (SMPE) are terms defined by ISO 13385-1:2019.

Note: Dedicated for outside measurement (depth bar is not fitted).

DIMENSIONS

